

Digital Voltmeter (0-100V) and Ammeter (10 A) Dual Led Voltage Current Measurement Module

Slug: digital-voltmeter-0-100v-and-ammeter-10-a-dual-led-voltage-current-measurement-module

(placeholder)

FRONT

(placeholder)

BACK

(placeholder)

DETAIL

(placeholder)

PINOUT

TECHNICAL SPECIFICATIONS & SUMMARY

Specifications:- Input Voltage - 4.5V to 30V DC Input Current - $\leq 20\text{mA}$ Display Color - Red (Voltage) , Blue (Current)
Measuring Voltage Range - 0V to 100V DC Measuring Current Range - 0A to 10A Measurement Accuracy - 1% Minimum
Voltage Resolution - 0.1V Minimum Current Resolution - 0.01A Size - 48x29x21mm Note:- Maximum Input Voltage should not exceed 30V otherwise there is a danger of burning Wiring:- Black line (thin): vacant or buck circuit (module) Negative Red line (thin): power supply Positive Black line (thick): COM, common measuring Red line (thick): PW+, measuring terminal voltage input positive Yellow line (thick): IN+, current input Positive Package Contains:- 1 x Digital Voltmeter & Ammeter Module 1 x Two wire thin connector 1 x Three wire thin connector

UNIT PRICE (EX. GST)

Rs. 105

WITH 18% GST

Rs. 124

In stock: 10 units - HSN: 85044090

Order online at uniksystem.in for bulk pricing.